



[\(https://www.highlite.com/en/\)](https://www.highlite.com/en/)

[\(https://www.highlite.com/en/\)](https://www.highlite.com/en/) / [Entertainment Lighting \(https://www.highlite.com/en/products/entertainment-lighting.html\)](https://www.highlite.com/en/products/entertainment-lighting.html) / [Light controllers \(https://www.highlite.com/en/products/entertainment-lighting/light-controllers.html\)](https://www.highlite.com/en/products/entertainment-lighting/light-controllers.html) / [DMX Gear \(https://www.highlite.com/en/products/entertainment-lighting/light-controllers/dmx-gear.html\)](https://www.highlite.com/en/products/entertainment-lighting/light-controllers/dmx-gear.html) / Showtec NET-2/5 Pocket

Product code:

50808

SHOWTEC NET-2/5 POCKET

2 Channel Artnet node, 5p XLR



<https://www.highlite.com>

The Showtec NET-2/3 Pocket and NET-2/5 Pocket nodes are cutting-edge network routing devices which convert ArtNET or sACN to DMX512 and back. The power input can be provided by POE which makes the 12V power supply superfluous.

A maximum of 1024 channels can be transported over a single CAT5. All settings can be done by the easy-to-use menu on the graphic display and buttons on the front.

Settings can also be arranged via the webbrowser possibility, which gives you (remote) access through your computer or laptop and your network. Default login account: Admin, password: Admin.

✓ Supports ArtNET and sACN protocol

✓ 2 universes DMX input or output

✓ Remote Setup Interface

✓ PoE (IEEE 802.3af)

R.R.P.

€ 179.00



[NEED ADVICE? \(HTTPS://WWW.HIGHLITE.COM/EN/CONTACT/\)](https://www.highlite.com/en/contact/)

Subtotal ex. vat

♥ **[ADD TO WISH LIST](#)**





SPECIFICATIONS



Configuration examples

- ArtNet to 2x DMX output
- 2x DMX input to ArtNet
- Clone 1 DMX inputs to 1x DMX output and Artnet
- HTP/LTP Merge 2x ArtNet to DMX output
- HTP/LTP Merge DMX input and ArtNet to DMX output

Connections

| | |
|----------------------------|-------------------------------------|
| Network | RJ45 |
| DMX | 2x 5-pin XLR |
| Supported protocols | ArtNET, sACN, TCP/IPv4, DMX-512A |
| Dimensions | 67 x 115 x 44 mm |
| Power supply | 12VDC, 500mA, or PoE (IEEE 802.3af) |
| Power consumption | 6W max. |
| Operating temp | 0 to +40 °C |
| Weight | 335gr |

CROSS REFERENCES



DOWNLOADS



RECENTLY VIEWED PRODUCTS